



PE07.12-P-2000-60I	Legend for wiring diagram of diesel injection system with in-line pump (IFI) and electronic control	ENGINE 606.964 in MODEL 463 up to 31.5.98	
--------------------	---	---	--

Item	Designation	Coordinate
A45	Horn/airbag clock spring contact	62G
A45x2	FAN relay module clock spring contact connector	62E
B5/1	Pressure sensor (EDS)	17L
B11/4	Coolant temperature sensor	5L
B17	IAT sensor	4L
B28/3	EGR [ARF] lifting sender	10L
B37	Pedal value sensor	15L
H2	Fanfare horns	38C 40C
K38/3	Starter lock-out relay module	46E
K40/3	Relay unit (diesel)	28L 42L 55L
K40/3f1	Differential lock fuse, run-on relay	54J
K40/3f2	IFI [ERE] engine management fuse (circuit 87)	28J
K40/3f6	Fanfare horn fuse	41J
K40/3k4	Fanfare horn relay	43K
K40/3k5	ETC [EGS], ABS, differential lock relay	55K
K40/3k8	IFI [ERE] engine management relay (circuit 87)	29K
L5/6	CKP sensor (IFI/DFI [ERE/EVE])	2L
N3/7	IFI [ERE] control module	9A 19A 29A 43A
N14	Preglow time relay	19E
N14/1	Run-on cooling relay	13L 55A
N15/3	ETC control module	60A
N47-7	ABS control module	56A
R9	Glow plugs	19L 20L 21L
S2/1	Ignition/starter switch	53A
S4/2	FAN switch	62L
S4/2x1	FAN switch connector	62H
S9/1	Stop lamp switch (4-pin)	26C 59A
S25/3	110 °C temperature switch	12L
S40	Cruise control switch	24L
S40x1	CC [TPM] switch connector	23H
S76	Differential lock switch group	58A
W3/2	Ground (left front wheelhousing)	40D
W12	Ground (center console)	9D 11D 21C 51E
W29/2	Ground (right A-pillar)	27D
W29/7	Ground (steering column)	14D 62A
X4/30	Terminal block (circuit 30, engine)	19C

X11/4	Data link connector (DTC readout)	43E
X12/3	Terminal block (circuit 30, 15, 61 (3-pin))	29D 50E
X31/5	CAN databus terminal (high)	48E
X31/6	CAN databus terminal (low)	49E
X35/63	Control module box/engine separation point	1E
Y1/1	Electrohydraulic shutoff actuator	8L
Y23/1	Fuel quantity actuator (IFI [ERE])	36F
Y27	EGR [ARF] switchover valve	30E
Y74	Pressure regulator valve	32E
Z6/8	Sensor ground connector sleeve	6H
Z50/1	Connector sleeve 1	25E
Z50/9	DFI [EVE] connector sleeve (circuit 87, unfused)	33D